



Auditory Systems

Instructions for the use of

E·A·RTONE[®] 5A

Insert Earphones



Aearo Ltd.
SK12 1FJ, UK

INTRODUCTION

Congratulations on the purchase of your new E-A-RTONE® 5A Insert Earphones. The E-A-RTONE® 5A was designed to retain all the advantages of the E-A-RTONE® 3A Insert Earphone, and provide additional features. The front tubes that conducted sound from the body level transducer of the 3A model to the ear canal, and the tubing or “plumbing” within the transducer case have been eliminated. The result is an insert earphone that provides ear-level sound transduction, a wider frequency response, and greater reliability.

Whether you are performing hearing screening in an educational or industrial setting, testing related to the fitting or evaluation of amplification, audiological research, or comprehensive diagnostic assessment, E-A-RTONE® 5A Insert Earphones provide many advantages that can enhance test reliability and minimize or eliminate problems frequently encountered with supra-aural headphones.

Because the subject’s external canal is sealed with an E-A-RLINK® foam plug, which functions as a sound delivery system while at the same time attenuating ambient noise, reliable threshold measurement can be accomplished in environments previously unsuitable for hearing testing.

Direct coupling also produces much greater sound separation between ears across the test frequency range. Clinically, that means more instances where the need for masking is eliminated, or the level necessary for effective masking is lower. Your average testing time will decrease without sacrificing reliability. The method of clinical masking you use does not need to be altered. Simply substitute the greater inter-aural attenuation values cited in the Obtained Interaural Attenuation table on page 4 of this booklet.

E-A-RLINK®, couplers are available from your distributor in five sizes, three foam tips and two small PVC tips for infant testing. The standard (3A) foam plug will comfortably fit most adult ear canals, a smaller (3B) size is appropriate for pediatric testing, and an extra large (3C) size can be used to couple the E-A-RTONE® Insert Earphone to very large or surgically altered ear canals. To accommodate EACs too small for the 3B tip, 3.5mm and 4.0mm PVC “Infant Eartips” are now available for your youngest patients. Disposable plugs insure that sanitary conditions exist for every test you perform, and that periodic cleaning of a headband or earphone cushion is no longer required.

The E-A-RTONE® 5A Insert Earphone is offered with two levels (10 and 50) of impedance to match the output of most commercially available audiometers. If you require a 300 insert earphone, the E-A-RTONE® 3A is

still available with that impedance. Your distributor or E-A-R Auditory Systems can help you determine which version is appropriate for your equipment.


E-A-RTONE® 5A Insert Earphones were designed to mimic the frequency response of the TDH-type earphone. It is strongly recommended, however, that the (RETSPL) values and procedure cited in the ANSI S3.6 - 1996 Standard be used in recalibration of your equipment, before initial use, unless your audiometer was purchased with an E-A-RTONE® 5A as the standard transducer. Subsequent calibrations should be performed at least annually thereafter. Measured correction factors can be applied in those cases where it is necessary to alternate between an insert earphone and a supra-aural earphone.

This instruction booklet is intended to provide information to allow you to perform hearing testing with your audiometer and E-A-RTONE® 5A Insert Earphones with the confidence that test results will be comparable to, or in certain instances more reliable than, measurements performed with supra-aural headphones. Most questions regarding the use and calibration of E-A-RTONE® 5A Insert Earphones can be answered by reviewing this booklet and the American National Standard *Specification for Audiometers (ANSI S3.6-1996)*. For information regarding replacement items, please contact your distributor or E-A-R Auditory Systems Customer Service at 317/656-5713. Requests for technical assistance, or comments regarding E-A-RTONE® 5A Insert Earphones should be directed to E-A-R Auditory Systems 5457 W. 79th Street, Indianapolis, IN 46268.

1. Preliminary Procedures for Use of the E-A-RTONE® 5A

Initially examine the ear canal for obstruction(s) and evaluate the proper size of E-A-RLINK® disposable foam eartip needed to fit the particular ear canal. Although the standard E-A-RLINK® 3A fits most adult ear canals, the smaller diameter E-A-RLINK® 3B eartips are available if the standard eartip is too large for full insertion in small external canals. A good seal and the proper insertion depth will afford the greatest ambient and interaural attenuation. Insertion procedures are the same for the E-A-RLINK® 3A and E-A-RLINK® 3B, but deep insertion may be difficult to achieve in extremely small ear canals. In these instances, the newly available Infant Eartips are appropriate.

- Secure the section of black tubing, which protrudes from the E-A-RLINK® eartip, to the sound tube nipple protruding from the E-A-RTONE® 5A case.
- Slowly roll the E-A-RLINK® tip into the smallest diameter possible and insert the E-A-RLINK® well into the ear canal (see illustrations). The case will function as an insertion tool. Since the eartips are 12 mm long, the correct insertion depth into the ear canal is obtained when the rear edge of the E-A-RLINK® is 2-3 mm inside the entrance of the ear canal.
- Hold E-A-RLINK® in the ear canal until expanded.
- After the test is completed, remove the E-A-RLINK® eartips and replace with a new pair for the next subject.




Full Insertion



Shallow Insertion

Proper insertion depth is necessary to achieve maximum ambient noise attenuation and interaural attenuation. The graph below depicts interaural attenuation as a function of insertion depth. The described interaural attenuation is obtained for each ear in which the E-A-RLINK® is fully inserted, regardless of whether it is the “sending” ear or “receiving” ear.



2. Background Noise Reduction

A major benefit of the E-A-RTONE® Insert Earphone in combination with the E-A-RLINK® disposable foam eartips is the reduction of background noise that might interact with the presented pure tones and influence threshold determinations. When E-A-RLINK® eartips are fitted to the subject according to the instructions, the expected noise attenuation will typically exceed 30 dB in the frequency region 125-8000 Hz. This additional attenuation will improve test reliability in non-ideal environments and, in most cases, allow testing down to 0 dB HL in a background noise level not exceeding 45 dB(A).

The current ANSI Standard (ANSI S3.1-1999) “Maximum Permissible Ambient Noise Levels (MPANLs) For Audiometric Test Rooms” (Table 1 and Table 2) includes octave band and one-third octave band permissible noise levels for both supra-aural and Insert Earphones. The ANSI octave band MPANLs are presented below for standard earphones and also for E-A-RTONES® with fully inserted E-A-RLINKS®.

ANSI S3.1-1999 - Ears covered: octave band MPANLs using a supra-aural or insert earphone for three test frequency ranges re: 20µPa to nearest 0.5 dB.

Octave Band Intervals	Supra-aural Earphone			E-A-RTONE Full Insertion		
	125 - 8,000 Hz	250 - 8,000 Hz	500 - 8,000 Hz	125 - 8,000 Hz	250 - 8,000 Hz	500 - 8,000 Hz
125	35.0	39.0	49.0	59.0	67.0	78.0
250	25.0	25.0	35.0	53.0	53.0	64.0
500	21.0	21.0	21.0	50.0	50.0	50.0
1000	26.0	26.0	26.0	47.0	47.0	47.0
2000	34.0	34.0	34.0	49.0	49.0	49.0
4000	37.0	37.0	37.0	50.0	50.0	50.0
8000	37.0	37.0	37.0	56.0	56.0	56.0

The ears covered MPANLs shown in the above table were derived using mean earphone attenuation values. To decrease the chance that individual listeners for whom less than average attenuation is obtained will experience threshold shift, the MPANLs can be lowered by reducing the amount of earphone attenuation. An appropriate reduction would be equal to the mean attenuation minus one standard deviation. The net effect would be that the MPANLs would be lower (more stringent) for ears covered testing. This reduction would cover about 84% of all subjects. The standard deviations for Insert Earphones for 125 to 8000 Hz are between three (3) and six (6) decibels. Please refer to ANSI S3.1 – 1999, Table A.2, for specific standard deviation values by frequency.

3. Positioning of the E-A-RTONE®

While the shape of the E-A-RTONE® 5A case is similar to that of a small BTE instrument, correct insertion of the connected E-A-RLINK® will place the case portion in front of the pinna. Always use E-A-RLINK® tips in both ears, or block the non-test ear with an E-A-R® foam plug.


4. Cable Assembly

The junction or pod portion of the cable assembly should be supported at or near the patient’s mid chest level to relieve tension on the E-A-RLINK® couplers. This can be accomplished by attaching the Velcro-backed clip to the pod and then clipping the pod directly to the subject’s clothing. Alternatively, the clip can be attached to the metal ring on the adjustable lanyard that is worn around the neck.

5. Pure Tone Calibration

When the E-A-RTONE® 5A Insert Earphone is to be used as the primary transducer, the audiometer should be recalibrated using the reference thresholds provided in ANSI S3.6-1996. The standard presents reference

thresholds for the HA-1, HA-2 (DB 0138) and Ear Simulator 2cc couplers. The Bruel & Kjaer 2cc DB-0138 (HA-2) coupler will simplify the calibration procedure and is recommended. Reference thresholds for the DB-0138, IEC 711, and HA-1 couplers are presented below. Should calibration be performed for an audiometer currently calibrated towards ISO-389, the reference thresholds in a 2cc DB-0138 coupler should be used. In order to calibrate the audiometer for direct readings of the hearing thresholds in dBHL using the reference thresholds, the following procedure is recommended. The instrumentation required is a Sound Level Meter with an appropriate condenser microphone calibrated according to the manufacturer's specification. To the microphone, a 2cc coupler, e.g., Bruel & Kjaer DB-0138 is attached. The white nylon tube nipple of the E-A-RTONE® 5A earphone is connected directly to the coupler (see illustration). Set the intensity dial on the audiometer to 70 dBHL and adjust the output from the audiometer to the SPL-values given for the different test frequencies in the table below. Repeat the procedure for all available test frequencies, and in case of a dual channel audiometer, for both channels.



ANSI S3.6-1996 and ISO 389-2:1994 Calibration Values			
Frequency in Hz	Coupler 2cc DB-0138	Coupler IEC 711	Coupler 2cc HA-1
125	96.0	98.0	96.5
250	84.0	87.5	84.5
500	75.5	79.5	76.0
750	72.0	76.0	72.0
1000	70.0	75.5	70.0
1500	72.0	79.5	70.0
2000	73.0	81.5	72.5
3000	73.5	83.0	72.5
4000	75.5	85.0	70.0
6000	72.0	86.0	67.5
8000	70.0	85.5	66.5

6. Correction Factors

Providers who need to switch between insert and supra-aural earphones may do so with properly calibrated equipment. Previously provided “out-of-the-box” correction factors, however, have been judged to be imprecise for clinical work, particularly when used with audiometers that have been calibrated to account for equipment changes over time. Standardized correction factors are therefore not provided. If the audiometer is calibrated for either type of transducer as the primary earphone, measured correction factors for a secondary earphone can be obtained by measuring the output on the appropriate coupler and calculating the difference from the appropriate target value at each frequency. Audiogram correction factors can then be confidently applied for the secondary earphone. The example below outlines the steps, and provides an example worksheet to calculate the correction factors by frequency where the audiometer is calibrated with a supra-aural earphone, and an insert earphone is used as the secondary transducer. In this case, the measured SPLs are the 2cc coupler values obtained with an insert earphone connected to an audiometer calibrated for a supra-aural earphone, and the Target SPLs are the audiometer HL setting plus the insert earphone RETSPLs for the particular 2cc coupler used. The process will work as well in reverse, i.e. audiometer calibrated for an E-A-RTONE® insert earphone with a supra-aural earphone as the secondary transducer, as long as the appropriate Target SPLs (TDH values) are employed.

- Calibrate the audiometer to the appropriate standard for the primary transducer. (TDH-39, 49 or 50 in this example)
- Connect E-A-RTONES® to the audiometer.
- Measure the output in a 2cc coupler and substitute obtained values for the Measured SPLs in the example worksheet below.
- Tabulate at each test frequency the difference between actual and target sound pressure levels.
- Apply the rounded correction factors obtained to the audiometer dial readings. Record and post for convenience.
- Repeat the procedure whenever the audiometer is calibrated.

Worksheet example for calculation of individual (insert earphone correction factors for audiometer calibrated with TDH type earphone										
Frequency in Hz										
	250	500	750	1000	1500	2000	3000	4000	6000	8000
Measured SPL	90.5	76.8	74.1	72.0	73.4	77.5	79.3	76.5	63.7	58.0
Target SPL*	84.0	75.5	72.0	70.0	72.0	73.0	73.5	75.5	72.0	70.0
Difference	6.5	1.3	2.1	2.0	1.4	4.5	5.8	1.0	-8.3	-12.0
Rounded Correction	5	0	0	0	0	5	5	0	-10	-10

*Target SPL = audiometer HL + RETSPL

7. Calibration for Speech Audiometry

ANSI S3.6-1996 specifies the 1 kHz reference-tone level for the speech circuit as 12.5 dB above the 1 kHz pure-tone reference test threshold for the earphone in question. Calibration of the E-A-RTONE® for speech is thus performed by setting a 1 kHz signal at 0 VU through the speech circuit, setting the attenuator to 60 dBHL, and adjusting for 72.5 (60.0 + 12.5) dB SPL in the 2cc coupler. A range of 69.5 to 75.5 dB meets the ±3 dB tolerance allowed in the standard.

8. Technical Specifications and Limits for E-A-RTONE® 5A

Impedance 10 Ohm or 50 Ohm

1 kHz Sensitivity..... 102.5 dB SPL in DB-0138 (HA-2) coupler
@ 0.1 Volt rms. (10 Ohm)
@ 0.2 Volt rms. (50 Ohm)

Limits ± 3 dB

Distortion..... < 3% measured @ 500 Hz, 118.5 dB
SPL

.....
Maximum output Meets or exceeds 110 dBHL at standard
audiometric frequencies between 500
and 4000 Hz

.....
Safe operating limits Max. continuous sine wave drive:
2.5 Volt rms. (10 Ohm)
5.0 Volt rms. (50 Ohm)

.....
Max. Peak voltage for 10 Volts (10 Ohm)
1-% duty cycle 20 Volts (50 Ohm)

Accessories supplied:
50 disposable E-A-RLINK® 3A eartips, 10 disposable E-A-RLINK® 3B eartips,
4 disposable E-A-RLINK® 3C eartips and 213 cm cord (7 feet) with left and
right 1/4" mono color-coded phono-plugs.

Data supplied: 2cc-coupler frequency response chart on individual units.

9. Reference Equivalent Threshold Sound Pressure Levels (RETSPLs) According to ANSI S3.6-1996 and ISO-389-2:1994

ANSI S3.6 and ISO 389-2 Reference Thresholds			
Sound Pressure Levels in dB re. 20 μ Pa			
Frequency in Hz	Coupler 2cc DB-0138	Coupler IEC 711	Coupler 2cc HA-1
125	26.0	28.0	26.5
250	14.0	17.5	14.5
500	5.5	9.5	6.0
750	2.0	6.0	2.0
1000	0.0	5.5	0.0
1500	2.0	9.5	0.0
2000	3.0	11.5	2.5
3000	3.5	13.0	2.5
4000	5.5	15.0	0.0
6000	2.0	16.0	-2.5
8000	0.0	15.5	-3.5

10. Limited Warranty


Aearo Company warrants each insert earphone (sold under the name E-A-RTONE[®] 5A) it manufactures to be free from defects in material and workmanship under normal use for a period of twelve (12) months from the date of sale to the original purchaser. During this warranty period Aearo Company Auditory Systems will repair or replace, at Auditory Systems sole option, free of charge, any defective part returned with shipping charges prepaid to the address listed on the back cover. This shall be the sole and exclusive remedy available for a failure under this warranty and for any and all claims arising out of the purchase and use of the product, and the sole obligation of Aearo Company under this warranty shall be limited to repair or replacement of any defective part. Please specify the serial number(s) of the product, original date of purchase, and the nature of the problem. Merchandise not returned prepaid will be refused. Mailing, at the time of purchase, a completed Warranty Card that is included with each E-A-RTONE Insert Earphone will facilitate our ability to return repaired units as quickly as possible. Warranty service will vary depending on the availability of parts and the workload. There will be charges rendered for product repairs made after our warranty period has expired (twelve [12] months from original date of purchase). Upon request, our Customer Service Department will provide cost estimates for post-warranty repairs.

Our warranty does not cover damage or failure caused by abuse, misuse, abnormal usage, faulty installation, improper maintenance, failure to follow

the operation and other instructions found in the written materials provided with the product, or repairs other than those made by Aearo Company Auditory Systems. There are no obligations or liabilities on the part of Aearo Company Auditory Systems for consequential damages arising out of, or in the connection with, the operation, use or performance of the product including, without limitation, with respect to loss of revenues or profit.

This Warranty is in lieu of all other oral or written, express or implied warranties including, without limitation, warranties of fitness for a particular purpose and merchantability, and there are no warranties that extend beyond the description or duration of this warranty. No representative, agent, dealer or employee of Aearo Company is authorized to give any other warranty or to assume for Aearo Company any other liability in connection with sale or service of the products covered by this limited warranty.

In order for Auditory Systems to properly evaluate and resolve potential problems with E-A-RTONE Insert Earphones it is necessary for the complete unit(s) i.e., cable and red and blue cases to be returned. Return of the cable or cases alone will impede our ability to repair insert earphones in a timely fashion. Complete units needing repair should be sent to the address on the back cover of this instruction book.



E-A-R Auditory Systems
8001 Woodland Drive
Indianapolis, IN 46278

Customer Service
(toll free from the US only): 800/624-5955 Fax: 877/807-7113

International Customer Service
Ph: 317/656-5713 Fax: 317/656-5760

Technical Support Ph: 317/692-6550 Fax: 317/692-6604

2000 Aearo Company Auditory Systems

E-A-R®, E-A-RTONE® and E-A-RLINK® are all registered trademarks of Aearo Company